전문적인 기능



Preset
라이브 사운드 강화를 위해 특별히 설계된 120채널의 Preset



Anti-Feedback Wizard
자동 피드백 제어 기능



RTA (Real Time Analyzer)
실시간으로 오디오 신호의 주파수 특성을 분석



Effects Wizard
이펙트를 설정하고 라우팅 할 수 있는 툴





Gain Wizard
입력 클리핑을 모니터링하고, 입력 게인 감소가 얼마나 필요한지 나타내주는 툴.



QSC Loudspeaker & Amp
K, K.2, KLA 또는 KW 스피커 및 GXD 시리즈 앰프에 대한 최적의 게인 설정 가능



Room Tuning Wizard
실에 대한 주파수 분석을 RTA로 나타내주는 툴



보안
다단계 암호 보안 시스템이 포함되어 있어 다른 운영자에게 원하는 만큼 제어 권한 부여 가능

원격제어



Tablet PC, Mobile App을 이용한 제어 가능




Follow Mixer
원격제어 장치 (Tablet or Mobile)가 믹서의 페이더 선택을 따라가는 설정

손쉬운 사용



Touch and Turn
빠르고 직관적인 터치 – 앤 – 턴 작업이 가능



매뉴얼 제공
믹서 화면에서 내장된 매뉴얼 확인 가능



Scene 설정 및 저장 가능



Simple Mode



Advanced Mode



Copy & Paste
출력에 설정된 채널 설정을 복사하여 다른 채널에 붙여넣기 가능

파워풀한 프로세싱

Studio Grade Effects Processing
고품질 이펙트 프로 세서 내장





Input Processing



Output Processing
TouchMix 8/16 : 8필터, Touchmix 30 : 12 필터

그룹설정 기능



DCA Group
입/출력 레벨 제어 가능



Mute Group

뛰어난 레코딩 (Only Touchmix-30 Pro)



DAW 유틸리티 제공



MP3 USB Playback



TouchMix-16



TouchMix-8

TOUCHMIX-16 20 in / 10 out	**TOUCHMIX-8** 12 in / 6 out
7" (178 mm) diagonal color TFT, capacitive touch sensing	7" (178 mm) diagonal color TFT, capacitive touch sensing
- Total : 22	- Total : 14
- Mic/Line : 16 (12 XLR, 4 XLR combo)	- Mic/Line : 8 (4 XLR, 4 XLR combo)
- Line : 2 Stereo, 1/4" TRS	- Line : 2 Stereo, 1/4" TRS
- Stereo USB : Stereo USB / MP3 playback	- Stereo USB : Stereo USB / MP3 playback
- Talkback : 1 (XLR)	- Talkback : N/A
- EQ : 4-band Parametric EQ with Hi/Low Shelving option, Variable 24 db/octave HPF and LPF	
- Dynamics : Gate, Compressor	- Dynamics : Gate, Compressor
- Delay : Delay (100 msec max)	- Delay : Delay (100 msec max)
- Total : 12	- Total : 6
- Main L/R : 2 (XLR line-level)	- Main L/R : 2 (XLR line-level)
- Aux : 6 (XLR, line-level) + 2 (TRS, stereo In-Ear Monitor or mono balanced line-level)	- Aux : 4 (XLR, line-level)
- in Ear Monitor (Stereo) : 2 (TRS, 16 ohm min. impedance, from Auxes 7/8 and 9/10)	- in Ear Monitor (Stereo) : 1 (TRS, 16 ohm min. impedance, from Auxes 3/4)
- Cue : 1 (Stereo, TRS, line or headphone, 16 ohm min. impedance)	- Cue : 1 (Stereo, TRS, line or headphone, 16 ohm min. impedance)
- Monitor L/R : 1 (Stereo TRS, line or headphone, 16 ohm min. impedance)	- Monitor L/R : N/A
- DCA : 8 (with Mutes)	- DCA : 8 (with Mutes)
- Mute : 8	- Mute : 8
- Sub Groups : N/A	- Sub Groups : N/A
USB Wi-Fi adaptor (included) or external Wi-Fi router (requires USB to ethernet adaptor)	USB Wi-Fi adaptor (included) or external Wi-Fi router (requires USB to ethernet adaptor)
Shipping : 12 cm x 62 cm x 38.1 cm / Mixer only : 5.8 cm x 36 cm x 29.1 cm	Shipping : 11.4 cm x 50.8 cm x 42 cm / Mixer only : 5.6 cm x 33.3 cm x 24.5 cm
Shipping : 4.9 kg / Mixer only : 2.98 kg	Shipping : 4.9 kg / Mixer only : 1.95 kg